

Product summary:

DiSEqC multiswitch with external power supply, SAT inputs attenuators, switchable active/passive terr. input

Brief description:

17in/52out standalone multiswitch for distribution of signals from terrestrial broadcasting and 4 satellites (16 SAT IF inputs) for up to 52 users. Switchable active/passive terrestrial input. External power supply (included). For use with Quattro LNB only!



Technical data:

Parameter	Condition	Value
Frequency range	Sat. inputs	950-2150 MHz
	Terr. input	5-840 MHz (passive), 40-840 MHz (active)
	Outputs	5-2150 MHz (passive), 40-2150 MHz (active)
Control		DiSEqC 1.0 (2.0)
Insertion loss	Sat.	5 dB (950 MHz) ~ 0 dB (2150 MHz)
	Terr. passive	27 dB avg
	Terr. active	2 dB gain avg
Sat. inputs isolation	Between V/H polarisations	20 dB min
	Between low/high bands	20 dB min
	Between sat. systems	25 dB min
Maximum input level*	Sat.	100 dB μ V avg
	Terr.	85 dB μ V avg (active),
Maximum output level*	Sat.	100 dB μ V avg
	Terr.	87 dB μ V avg (active)
Power consumption	From each receiver	100 mA (18 V)
	From external power supply	11W (passive) + LNB 12W (active) + LNB
Dimensions (w,d,h)		35.5 x 44.0 x 5.0 cm
Temperature range		-25 ~ +50 °C
Weight		3.670 kg

*Terr.: EN 50083-3/60dB IMA3 [dB μ V]; SAT: EN 50083-3/35dB IMA3 [dB μ V]

Postal address: EMP-Centauri s.r.o. 5. května 690 339 01 Klatovy Czech Republic

Management: Tel.: +420 376 323 813 Tel.: +420 603 497 419 E-mail: info@emp-centauri.cz

Sales department: Tel.: +420 376 323 813 Tel.: +420 603 497 419 Tel.: +420 776 619 976 (EN) Tel.: +420 778 066 654 (CZ) E-mail: sales@emp-centauri.cz

Purchase department: E-mail: purchase@emp-centauri.cz

Technical support: Tel.: +420 376 323 853 (during workhours) Hotline: +420 603 497 419 (available anytime) E-mail:

support@emp-centauri.cz Skype ID : live:.cid.624e3941fb5334d9