

Product summary

DiSEqC multiswitch with external power supply, passive terr. input

Brief description

17in/30out standalone multiswitch for distribution of 16 SAT IF signals including passive terrestrial for up to 30 users. The multiswitch is DC supplied from connected satellite receivers, DC2.1 socket for external power is connected to all satellite inputs. Power supply PA12 2A is included in the package.



Technical data

Parameter	Condition	Value
Frequency range	LNB inputs	950-2150 MHz
	Terr. input	40-862 MHz
	Outputs	40-2150 MHz
Control		DiSEqC 1.0 (2.0) commands
Insertion loss	Sat.	5dB avg.
	Terr.	30 dB avg.
Sat. inputs isolation	Between V/H polarisations	20 dB min
	Between low/high bands	25 dB min
	Between sat. systems	25 dB min
Maximum input level*	Sat.	105 dB μ V avg
	Terr.	105 dB μ V avg
Maximum output level*	Sat.	100 dB μ V avg
	Terr.	75 dB μ V avg
Current_consumption	From each receiver	100 mA (18 V)
Dimensions (w,d,h)		18.6 x 33.2 x 5.1 cm
Temperature range		-25 ~ +60 °C
Weight		1.83 kg

Postal address: EMP-Centauri s.r.o. 5. května 690 339 01 Klatovy Czech Republic

Management: Tel.: +420 376 323 813 Tel.: +420 603 497 419 E-mail: info@emp-centauri.cz

Sales department: Tel.: +420 376 323 813 Tel.: +420 603 497 419 Tel.: +420 776 619 976 (EN) Tel.: +420 778 066 654 (CZ) E-mail: sales@emp-centauri.cz

Purchase department: E-mail: purchase@emp-centauri.cz

Technical support: Tel.: +420 376 323 853 (during workhours) Hotline: +420 603 497 419 (available anytime) E-mail: support@emp-centauri.cz Skype ID : **live::cid.624e3941fb5334d9**