

G1/1ECN-1 (E.116)**Product summary:**

DiSEqC 1.0 fixed position generator

Brief description:

1in/1out DiSEqC 1.0 generator for setting fixed satellite position. The unit is preset from factory for satellite position B (G1/1ECNpos-1), C (G1/1ECNopt-1) or D (G1/1ECNposopt-1). Connect the generator between receiver and device to be controlled.

**Technical data:**

Parameter	Condition	Value
Frequency range		950-2150 MHz
Insertion loss		2 dB avg
Generated DiSEqC commands	G1/1ECNpos-1	Position 1 & Option 0
	G1/1ECNopt-1	Position 0 & Option 1
	G1/1ECNposopt-1	Position 1 & Option 1
Power consumption		30 mA
Dimensions (w,d,h)		7.6 x 6.0 x 3.2 cm
Temperature range		-25 ~ +60 °C
Weight		0.070 kg