

S8/2PCN-W2 (P.167-W)**Product summary:**

Double DiSEqC 2.0 LNB switch

Brief description:

8in/2out double DiSEqC 2.0 switch for up to 4 satellite positions and 2 subscribers (or 2 tuners). It is designed for switching between 3 or 4 Twin LNBs, which are addressed in receiver's menu as DiSEqC 1.0 setting A/B/C/D.

**Technical data:**

Parameter	Condition	Value
Frequency range	Sat. inputs	950-2300 MHz
	Output	5-2300 MHz,
Control		DiSEqC 1.0 (2.0) commands "Position" & "Option"
Insertion loss		4 dB max
Sat. inputs isolation		25 dB min
Power consumption	From each receiver	35 mA (18V) + LNB
	DC current pass	400 mA max
Dimensions (w,d,h)		11.2 x 11.2 x 4.9 cm
Temperature range		-30 ~ +70 °C
Weight		0.290 kg